




JC14 Rec'd PCT/PTO 18 JAN 2002

FORM PTO-1390 (Modified) (REV 5-93)		U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE		ATTORNEY'S DOCKET NUMBER	
TRANSMITTAL LETTER TO THE UNITED STATES DESIGNATED/ELECTED OFFICE (DO/EO/US) CONCERNING A FILING UNDER 35 U.S.C. 371				040373-0316	
				U.S. APPLICATION NO. (If none, see 37 CFR 1.5) Unassigned 10/031346	
INTERNATIONAL APPLICATION NO. PCT/JP00/04882		INTERNATIONAL FILING DATE 21 July 2000		PRIORITY DATE CLAIMED 21 July 1999	
TITLE OF INVENTION METHOD OF AND APPARATUS FOR PATH SEARCH					
APPLICANT(S) FOR DO/EO/US Sei HIRADE					
Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information:					
<p>1. <input checked="" type="checkbox"/> This is a FIRST submission of items concerning a filing under 35 U.S.C. 371.</p> <p>2. <input type="checkbox"/> This is a SECOND or SUBSEQUENT submission of items concerning a filing under 35 U.S.C. 371.</p> <p>3. <input type="checkbox"/> This express request to begin national examination procedures (35 U.S.C. 371(f)) at any time rather than delay examination until the expiration of the applicable time limit set in 35 U.S.C. 371(b) and PCT Articles 22 and 39(1).</p> <p>4. <input checked="" type="checkbox"/> A proper Demand for International Preliminary Examination was made by the 19th month from the earliest claimed priority date.</p> <p>5. <input checked="" type="checkbox"/> A copy of the International Application as filed (35 U.S.C. 371(c)(2)) <input type="checkbox"/> is transmitted herewith (required only if not transmitted by the International Bureau). <input checked="" type="checkbox"/> has been transmitted by the International Bureau. <input type="checkbox"/> is not required, as the application was filed in the United States Receiving Office (RO/US)</p> <p>6. <input checked="" type="checkbox"/> A translation of the International Application into English (35 U.S.C. 371(c)(2)).</p> <p>7. <input checked="" type="checkbox"/> Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3)) <input type="checkbox"/> are transmitted herewith (required only if not transmitted by the International Bureau). <input type="checkbox"/> have been transmitted by the International Bureau. <input type="checkbox"/> have not been made; however, the time limit for making such amendments has NOT expired. <input checked="" type="checkbox"/> have not been made and will not be made.</p> <p>8. <input type="checkbox"/> A translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)).</p> <p>9. <input checked="" type="checkbox"/> An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).</p> <p>10. <input type="checkbox"/> A translation of the annexes to the International Preliminary Examination Report under PCT Article 36 (35 U.S.C. 371(c)(5)).</p> <p>11. <input type="checkbox"/> Applicant claims small entity status under 37 CFR 1.27.</p>					
Items 12. to 17. below concern other document(s) or information included:					
<p>12. <input checked="" type="checkbox"/> An Information Disclosure Statement under 37 CFR 1.97 and 1.98.</p> <p>13. <input checked="" type="checkbox"/> An assignment document for recording. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included.</p> <p>14. <input type="checkbox"/> A FIRST preliminary amendment. <input type="checkbox"/> A SECOND or SUBSEQUENT preliminary amendment.</p> <p>15. <input type="checkbox"/> A substitute specification.</p> <p>16. <input type="checkbox"/> A change of power of attorney and/or address letter.</p> <p>17. <input checked="" type="checkbox"/> Other items or information: Application Data Sheet</p>					

U.S. APPLICATION NO. (If known, use 37 CFR 1.55) Unassigned		10/031346		INTERNATIONAL APPLICATION NO. PCT/JP00/04882		ATTORNEY'S DOCKET NUMBER 040373-0316	
18. <input checked="" type="checkbox"/> The following fees are submitted:						CALCULATIONS	
Basic National Fee (37 CFR 1.492(a)(1)-(5): Search Report has been prepared by the EPO or JPO.....\$890.00							
International preliminary examination fee paid to USPTO (37 CFR 1.482).....\$710.00							
No international preliminary examination fee paid to USPTO (37 CFR 1.482) but international search fee paid to USPTO (37 CFR 1.445(a)(2))\$740.00							
Neither international preliminary examination fee (37 CFR 1.482) nor International search fee (37 CFR 1.445(a)(2)) paid to USPTO\$1,040.00							
International preliminary examination fee paid to USPTO (37 CFR 1.482) and all claims satisfied provisions of PCT Article 33(2)-(4)\$100.00							
ENTER APPROPRIATE BASIC FEE AMOUNT =						\$890.00	
Surcharge of \$130.00 for furnishing the oath or declaration later than 20 Months from the earliest claimed priority date (37 CFR 1.492(e))							
Claims	Number Filed		Included in Basic Fee		Extra Claims		Rate
Total Claims	17	-	20	=	0	x	\$18.00
Independent Claims	3	-	3	=	0	x	\$84.00
Multiple dependent claim(s) (if applicable)							\$280.00
TOTAL OF ABOVE CALCULATIONS =							\$890.00
Reduction by 1/2 for filing by small entity, if applicable.							\$0.00
SUBTOTAL =							\$890.00
Processing fee of \$130.00 for furnishing English translation later the 20 months from the earliest claimed priority date (37 CFR 1.492(f)).						+	
TOTAL NATIONAL FEE =							\$890.00
Fee for recording the enclosed assignment (37 CFR 1.21(h)). The assignment must be accompanied by an appropriate cover sheet (37 CFR 3.28, 3.31). \$40.00 per property +							\$40.00
TOTAL FEES ENCLOSED =							\$930.00
						Amount to be:	
						refunded \$	
						charged \$	
a. <input checked="" type="checkbox"/> A check in the amount of \$930.00 to cover the above fees is enclosed.							
b. <input type="checkbox"/> Please charge my Deposit Account No. <u>19-0741</u> in the amount of \$0.00 to the above fees. A duplicate copy of this sheet is enclosed.							
c. <input checked="" type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any overpayment to Deposit Account No. <u>19-0741</u> . A duplicate copy of this sheet is enclosed.							
NOTE: Where an appropriate time limit under 37 CFR 1.494 or 1.495 has not been met, a petition to revive (37 CFR 1.137(a) or (b)) must be filed and granted to restore the application to pending status.							
SEND ALL CORRESPONDENCE TO:							
Foley & Lardner Customer Number: 22428  22428 PATENT TRADEMARK OFFICE				 SIGNATURE  NAME DAVID A. BLUMENTHAL REGISTRATION NUMBER 26,257 Reg. No. 38,819			

7/PRTS

10/031346
531 Rec'd PCT 18 JAN 2002

DESCRIPTION

METHOD OF AND APPARATUS FOR PATH SEARCH

Technical field:

5 The present invention relates to a method of and an apparatus for searching for a certain path from a plurality of paths by interpolating a reception signal in radio communications. More particularly, the present invention relates to a method of and an apparatus for path
10 search to remove the effect of multipath fading by interpolating a reception signal of a code division multiple access (CDMA) system, for example.

Background art:

In recent years, mobile communication systems such as
15 portable telephone systems have been in widespread use as multifunctional inexpensive communication systems because of the advanced semiconductor technology and mobile communication technology. Multiplexing schemes that have heretofore been available for mobile communication systems,
20 typically portable telephone systems, include frequency division multiple access (FDMA) and time division multiple access (TDMA) schemes. Recently, there has been put to use a CDMA mobile communication system, which is capable of multiplexing more channels in the same frequency range
25 than the above multiplexing schemes, as a next-generation mobile communication technology.

According to the CDMA mobile communication system, a transmission signal is spread at the transmission side into a wide frequency range using an inherent spreading code that is allotted to the signal, and a reception
5 signal is despread (demodulated) using the same spreading code at the reception side. As a result, it is possible to mix a plurality of channels spread by respective inherent spreading codes from a plurality of users in one frequency band.

10 In a mobile communication system, a transmission signal from the transmission side is generally subject to multipath fading in its propagation. Specifically, a reception side receives a combination of waves propagating over different paths and received at different time
15 instants, i.e., direct and reflected waves propagating through different paths. The effect of such multipath fading needs to be removed in order to improve the reception quality. A path search device in a base station apparatus of a mobile communication system interpolates a
20 reception signal to increase the accuracy of path detection to detect a received wave over a certain path for thereby efficiently removing the effect of multipath fading.

For example, a path search device in a base station
25 apparatus of a CDMA mobile communication system is constituted as a searcher of the base station apparatus.

The searcher interpolates the reception signal to reduce chip intervals of the reception signal to detect a reception time instant at which a signal is to be received.

The base station apparatus also has fingers associated with the searchers for extracting certain paths from the reception signal based on the reception time instant detected by the searchers and performing RAKE combining.

Fig. 1 schematically shows an arrangement of a conventional base station apparatus in a CDMA mobile communication system. Here, only the reception function portion of the base station apparatus is illustrated.

Base station apparatus 10 comprises antenna 11 for receiving a transmission signal that has been spread according to CDMA scheme from a mobile terminal on a transmission side, not shown, receiver 12 having an interface function for a signal received by antenna 11 and demodulating the reception signal, parameter manager 13 for allotting spreading codes to respective communication channels (CHs) and managing the spreading codes, N searchers 14_1 to 14_N and N fingers 15_1 to 15_N for being allotted to the respective communication channels by parameter manager 13, and reception processor 16 for performing a predetermined reception process on the reception signal over certain paths extracted by fingers 15_1 to 15_N . Searchers 14_1 to 14_N and fingers 15_1 to 15_N are associated with each other in one-to-one correspondence.

transmission data are spectrum-spread using an inherent spread code for the communication channel. The transmission signal thus spread using respective inherent spreading codes in the CDMA system are received by antenna 5 11 of the base station apparatus. Receiver 12 performs signal interface conversion such as amplification and quadrature demodulation, e.g., multiplies a reception signal received by antenna 11 by a reference frequency which is generated by a reference frequency generator, not 10 shown, with a multiplier, not shown, thereby converting the reception signal into a baseband signal.

Parameter manager 13 is arranged to allot a finger and a searcher to each of communication channels included in the reception signal. For example, parameter manager 15 13 allots unused fingers and searchers, successively from first finger 15₁ and first searcher 14₁, to respective communication channels. Then, parameter manager 13 indicates code generating information for generating corresponding spreading codes to the allotted fingers and 20 searchers, which generate spreading codes that are associated with the code generating information indicated thereto.

Demodulated signal that is demodulated in receiver 12 is supplied to the searchers and fingers that have been 25 allotted by parameter manager 13.

Each searcher interpolates sampling points in order

to reduce chip intervals of the reception signal, and generates a delay profile based on the pilot signals added to the leading positions of the time slots of the interpolated signal. In the delay profile, the power values of reception signal components which are orthogonal to each other that are demodulated by receiver 12 are calculated for respective delay times in order to indicate a temporal change of reception time instants of the demodulated signal due to multipath fading. Usually, the power values calculated for the respective delay times on the delay profile represent peaks on a plurality of different propagating paths due to the effect of the multipath fading. Each searcher then detects peaks in excess of a predetermined threshold, and indicates delay times corresponding to the detected peaks to the finger associated therewith. The finger thus notified then extracts path of the received wave corresponding to the indicated delay time from the demodulated signal produced by receiver 12. The extracted paths are then RAKE-combined and then processed by reception processor 16.

Since the accuracy with which to detect paths depends upon the searchers, the searchers determine the reception quality of the base station apparatus. The arrangement of searchers will be described below. Because searchers 14_1 to 14_N are structurally identical to each other, the arrangement of first searcher 14_1 will be described. Fig.

2 shows the arrangement of first searcher 14₁.

First searcher 14₁ comprises first interpolating filter 20 for interpolating sampling points of the demodulated signal from receiver 12 to reduce chip intervals thereof, correlation value calculator 21 for calculating a correlation value of data interpolated by first interpolating filter 20, in-phase adder 22 and power adder 23 for generating a delay profile based on the calculated correlation value, second interpolating filter 24 for further reducing chip intervals of the generated delay profile, path controller 25 for indicating paths to be extracted to a corresponding finger, and code generator 26 for generating a spreading code for the calculation of the correlation value.

The interpolating filters will be described below. Fig. 3 shows a structure of first interpolating filter 20. It is assumed that the oversampling number is "2" and the tap length is "4". First interpolating filter 20 has first to seventh delay elements 27₁ to 27₇, first to eighth multipliers 28₁ to 28₈, and adder 29. First to seventh delay elements 27₁ to 27₇ are connected in series with each other. Input signals applied to first to seventh delay elements 27₁ to 27₇ and an output signal from seventh delay element 27₇ are supplied respectively to first to eighth multipliers 28₁ to 28₈. To first to eighth multipliers 28₁ to 28₈, there are applied respective predetermined filter

coefficients C_{-4} , C_{-3} , C_{-2} , C_{-1} , C_1 , C_2 , C_3 , C_4 , which are multiplied by the input signals applied to respective delay elements and the output signal from seventh delay element 27,. Assuming $i=1$ to 4, the filter coefficients C_{-i} and C_i are equal to each other. Products produced by respective multipliers 28₁ - 28₈ are added to each other by adder 29, which is then supplied as output signal 31 of interpolating filter 20 to the outside.

First interpolating filter 20 thus constructed can determine an interpolation point using values of the input signal at four points before and after input signal 30. As input signal 30 are more delayed, the input signal is shifted and interpolating points are successively determined. The interpolated serial interpolating data are supplied as output signal 31 to correlation value calculator 21 (Fig. 2).

Referring back to Fig. 2, based on the code generating information corresponding to the communication channel allotted from the parameter manager to first searcher 14₁, code generator 26 generates a spreading code corresponding to the communication channel. Correlation value calculator 21 detects the pilot signals added to the leading positions of respective time slots from the interpolation data interpolated by first interpolating filter 20 shown in Fig. 3, and generates ideal reception signals by spreading pre-recognized pilot signals with the

spreading code generated by code generator 26.

Correlation value calculator 21 then multiplies the detected pilot signals and the generated ideal reception signals to calculate correlation values thereby performing
5 quadrature demodulation on the pilot signals. As a result of the quadrature demodulation, the pilot signals are outputted as I (In-Phase) signals and Q (Quadrature-Phase) signals which are orthogonal to each other. In-phase adder 22 performs a certain number of in-phase additions
10 "I+I", and "Q+Q" on the I signal component and the Q signal component from correlation value calculator 21.

Power adder 23 performs a certain number of power additions " I^2+Q^2 " on the output from in-phase adder 22. Second interpolating filter 24, which is of the same
15 structure as first interpolating filter 20, interpolates added power data in order to further reduce chip intervals. Path controller 25 refers to a delay profile in which reception signals interpolated and expressed as power values by second interpolating filter 24 are arranged with
20 respect to respective delay times, detects peaks in excess of a predetermined threshold value, and indicates delay times corresponding to the detected peaks to first finger 15₁.

First searcher 14₁ thus arranged has a central
25 processing unit (CPU), not shown, which can execute various control processes based on a control program

stored in a given storage device such as a read-only memory (ROM) or the like.

Fig. 4 shows the content of the processing of the control program which is stored in such a given storage device. In first searcher 14₁, modulated signals from receiver 12 are interpolated at "1/2" chip intervals, for example, in first interpolating filter 20 as step S33. To do so, the oversampling number in the interpolating filter of the constitution shown in Fig. 3 may be set to "2". Then, in step S44, respective correlation values are calculated in correlation value calculator 21 for pilot signals which are of predetermined fixed patterns added to the leading positions of time slots, of the I and Q signals that have been interpolated at the "1/2" chip intervals. Because the pilot signals are of predetermined fixed patterns, it is possible to accurately determine ideal waveforms at the reception side. In correlation value calculator 21 calculates, correlation values with respect to ideal reception signals produced by spreading pre-recognized pilot signals with spreading codes generated by code generator 26 are calculated in the respective time slots of a received frame. A higher correlation value represents that the waveform of the pilot signal at the leading position of each time slot is closer to an ideal waveform, indicating a better reception sensitivity.

The calculated correlation values are added a given number of times N for I and Q signal components by in-phase adder 22, thus removing noise components contained in the I and Q signals, in step S35. The greater the
5 number of in-phase additions, the smaller the noise components of the I and Q signal components.

The result of the in-phase additions is then added for power a given number of times M by the power adder 23 in step S36. The power values are thus averaged with
10 respect to time, preventing paths from being detected with wrong power values due to instantaneous noise.

The values of in-phase additions are further interpolated at "1/4" chip intervals, for example, by second interpolating filter 24 in step S37. As described
15 above, second interpolating filter 24 is of a structure similar to first interpolating filter 20.

The calculated power values represent a delay profile on a temporal axis which indicates reception signals that are converted into power values for respective delay times.
20 Path controller 25 detects peaks in excess of a predetermined threshold, of the power values for respective delay times. Path controller 25 then indicates the delay times corresponding to the peaks in excess of the threshold to first finger 15, in step S38.

25 As described above, each of the searchers including first finger 15, performs an interpolation process to

increase the number of sampling points for increasing the accuracy of a subsequent process in order to achieve a higher accuracy for path detection.

In the conventional path searching apparatus
5 described above, the accuracy for path detection is increased by the interpolation by first and second interpolating filters 20, 24 in steps S33, S37. The number of interpolating operations is greater if they are performed before correlation values are calculated and in-
10 phase additions are made than if they are performed before correlation values are calculated and after power additions are performed in searchers 14_1 to 14_N as in steps S33, S37, resulting in an increased accuracy for path detection. Presently, however, because of a limitation
15 posed on the calculation amount allowed by the searchers, interpolating operations are performed before correlation values are calculated and after power additions are made as in steps S33, S37. The number of interpolating operations increases and the amount of subsequent
20 processing increases due to the interpolating operations also increases. As a result, there is a trade-off between the accuracy for path detection and the amount of processing.

The calculation processing in searchers 14_1 to 14_N
25 varies with time depending on the number of communication channels to be processed. Heretofore, however,

interpolating operations have fixedly been performed before correlation values are calculated and after power additions are performed, irrespective of the number of communication channels to be processed. Specifically, if
5 the number of communication channels to be processed by the searchers is small, there is a situation where an extra amount of calculation is available for performing interpolating operations before correlation values are calculated and in-phase additions are made. Heretofore,
10 since interpolating operations are performed in a fixed sequence, the number of interpolating operations is small, making it impossible to increase the accuracy for path detection.

Japanese laid-open patent publication No. Hei 10-
15 190522 (JP, A, 10190522) discloses a technique with respect to a path searching apparatus for using a matched filter to select signals, greater than a predetermined threshold, of all multipath signals in a multipath search range and perform a RAKE combining on the selected signals
20 for thereby combining all multipaths, and excluding the RAKE combining in chip phases where the signal level is low according to a threshold judgment using an average delay profile. According to the disclosed technique, it is also necessary to carry out processing operations in
25 the range of all searched paths at all times regardless of the number of communication channels to be processed. The

disclosed path searching apparatus is usually optimized to maintain a certain level of accuracy in a maximum allowable range. However, it is desirable for the path searching apparatus to have as good an accuracy for path
5 detection as possible if the number of communication channels is small and an extra amount of calculation is available.

Disclosure of the invention:

It is a first object of the present invention to
10 provide a path searching method of increasing the accuracy for path detection depending on the number of communication channels to be processed.

It is a second object of the present invention to
15 provide a path searching apparatus for increasing the accuracy for path detection depending on the number of communication channels to be processed.

The first object can be achieved by a method of searching for a path, comprising:

a first interpolating step of interpolating a
20 demodulated signal to generate a first interpolated signal;

a first selecting step of generating a first selected signal by alternatively selecting the first interpolated signal or the demodulated signal based on interpolation
25 information, said interpolation information indicating whether an interpolation process for reducing a chip

interval is to be performed or not between processes for generating a delay profile which indicates a temporal change of reception time instants of the demodulated signal due to multipath fading;

5 a correlation value calculating step of calculating a correlation value between a pilot pattern which is included in the first selected signal and has a predetermined fixed pattern and a predetermined expected value;

10 a second interpolating step of interpolating the correlation value calculated in the correlation value calculating step to generate a second interpolated signal;

 a second selecting step of generating a second selected signal by alternatively selecting the second
15 interpolated signal and the correlation value based on the interpolation information;

 an in-phase adding step of adding in-phase components of the second selected signal for a predetermined number of times;

20 a third interpolating step of interpolating an in-phase addition sum calculated in the in-phase adding step to generate a third interpolated signal;

 a third selecting step of generating a third selected
25 signal by alternatively selecting the third interpolated signal or the in-phase addition sum based on the interpolation information;

a power adding step of adding power values calculated from signal components of the third selected signal for a predetermined number of times;

5 a fourth interpolating step of interpolating a power addition sum calculated in the power adding step to generate a fourth interpolated signal;

10 a fourth selecting step of generating a fourth selected signal by alternatively selecting the fourth interpolated signal or the power addition sum based on the interpolation information; and

a path detecting step of detecting a path in excess of a predetermined threshold based on the fourth selected signal.

15 The second object can be achieved by an apparatus for searching for a path, comprising:

20 path searching means for generating a delay profile based on a pilot signal which is included in each time slot and has a fixed pattern, according to a path searching process composed of a plurality of processing units, the delay profile indicating a temporal change of reception time instants due to multipath fading of a demodulated signal;

25 interpolation information storage means for storing interpolation information indicative of whether an interpolation process for reducing a chip interval is to be performed or not before and after each of the

processing units;

interpolation position processing control means for enabling the path searching means to perform an interpolation process before and after each of the
5 processing units based on the interpolation information; and

path detecting means for detecting a reception path based on the delay profile generated by the path searching means.

10 The second object can also be accomplished by an apparatus for searching for a path, comprising:

interpolation information storage means for storing interpolation information indicative of whether an interpolation process for reducing a chip interval between
15 processes for generating a delay profile is to be performed or not, the delay profile indicating a temporal change of reception time instants of a demodulated signal due to multipath fading;

first interpolating means for interpolating the
20 demodulated signal to generate a first interpolated signal;

first selecting means for generating a first selected signal by alternatively selecting the first interpolated signal or the demodulated signal based on the
25 interpolation information;

correlation value calculating means for calculating a

correlation value between a pilot pattern which is included in the first selected signal and has a predetermined fixed pattern and a predetermined expected value;

5 second interpolating means for interpolating the corrected value calculated by the correlation value calculating means to generate a second interpolated signal;

10 second selecting means for generating a second selected signal by alternatively selecting the second interpolated signal and the correlation value based on the interpolation information;

15 in-phase adding means for adding in-phase components of the second selected signal for a predetermined number of times;

 third interpolating means for interpolating an in-phase addition sum calculated by the in-phase adding means to generate a third interpolated signal;

20 third selecting means for generating a third selected signal by alternatively selecting the third interpolated signal or the in-phase addition sum based on the interpolation information;

25 power adding means for adding power values calculated from signal components of the third selected signal for a predetermined number of times;

 fourth interpolating means for interpolating a power

addition sum calculated in the power adding means to generate a fourth interpolated signal;

fourth selecting means for generating a fourth selected signal by alternatively selecting the fourth
5 interpolated signal or the power addition sum based on the interpolation information; and

path detecting means for detecting a path in excess of a predetermined threshold based on the fourth selected signal.

10 In the present invention, the demodulated signal is typically a signal produced by converting a reception signal of a CDMA (Code Division Multiple Access) system into a baseband signal and processing the baseband signal by way of quadrature demodulation. The interpolation
15 information may preferably comprise information indicative of whether an interpolation process is to be performed or not depending on the number of communication channels to be processed, or information indicative of whether an interpolation process is to be performed or not depending
20 on the reception quality measured in each communication channel of the demodulated signal.

Brief description of the drawings:

Fig. 1 is a block diagram showing an arrangement of a conventional base station apparatus in a mobile
25 communication system of CDMA scheme;

Fig. 2 is a block diagram showing an arrangement of

an essential portion of a searcher in the base station apparatus shown in Fig. 1;

Fig. 3 is a block diagram showing an arrangement of an essential portion of an interpolating filter;

5 Fig. 4 is a flowchart schematically showing a processing sequence carried out by the searcher shown in Fig. 2;

Fig. 5 is a block diagram schematically showing an arrangement of a base station apparatus in a mobile communication system of CDMA scheme which incorporates a path searching apparatus according to a first embodiment of the present invention;

Fig. 6 is a block diagram showing an arrangement of an essential portion of the path searching apparatus according to the first embodiment of the present invention;

Fig. 7 is a diagram showing an example of interpolation information stored in an interpolation information memory;

20 Fig. 8 is a diagram showing an example of a format structure of interpolation position indicating information in the path searching apparatus according to the first embodiment;

Fig. 9 is a flowchart schematically showing a processing sequence carried out by a searcher in the path searching apparatus according to the first embodiment;

Fig. 10 is a block diagram showing an arrangement of an essential portion of a path searching apparatus according to a second embodiment of the present invention; and

5 Fig. 11 is a flowchart schematically showing a processing sequence carried out by a searcher in the path searching apparatus according to the second embodiment.

Best mode for carrying out the invention:

Preferred embodiments of the present invention will
10 be described in detail below.

First Embodiment:

An arrangement of a base station apparatus in a mobile communication system of CDMA scheme to which a path searching apparatus according to a first embodiment of the present invention is applied is schematically shown in Fig.
15 5. Here, only a receiving function section of the base station apparatus is illustrated. Those components shown in Fig. 5 which are identical to those shown in Fig. 1 are denoted by identical reference characters.

20 Base station apparatus 40 comprises antenna 11 for receiving a transmission signal that has been spread according to the CDMA scheme from a mobile terminal on a transmission side, not shown, and receiver 12 having an interface function for a signal received by antenna 11 and
25 demodulating the reception signal. Base station apparatus 40 also comprises parameter manager 41 for allotting

inherent spreading codes to respective communication channels (CH) and managing the spreading codes, N searchers 42_1 to 42_N and N fingers 43_1 to 43_N for being allotted to the respective communication channels by parameter manager 41, reception processor 16 for performing a predetermined reception process on the reception signal over certain paths extracted by fingers 43_1 to 43_N , and interpolation position controller 44 for changing interpolation positions of interpolating processes upon path searching in the searchers.

N searchers 42_1 to 42_N are structurally identical to each other. Here, an arrangement of first searcher 42_1 will be described below.

As shown in Fig. 5, first searcher 42_1 comprises code generator 45, path search processor 46, path controller 47, and interpolating filter 48. Code generator 45 generates a spreading code for the communication channel allotted by parameter manager 41. Path search processor 46 has correlation value calculator 21, in-phase adder 22, and power adder 23.

N finger 43_1 to 43_N are structurally identical to each other. Here, an arrangement of first finger 43_1 will be described below.

First finger 43_1 comprises code generator 52 for generating a spreading code for the communication channel allotted by parameter manager 41, a despreader 53 for

extracting a particular path corresponding to a delay time indicated by first searcher 42₁ from a demodulated signal from receiver 12 and despreading the signal from the extracted path with the spreading code generated by code generator 52, a detector 54 for performing channel estimation and removing the effect of fading, and a RAKE combiner 55 for combining detected signals.

Details of searchers 42₁ to 42_N and fingers 43₁ to 43_N, as exemplified by first searcher 42₁ and first finger 43₁, will be described below.

First searcher 42₁ is supplied with an interpolation position control signal from interpolation position controller 44. According to the interpolation position control signal, first searcher 42₁ allows interpolating filter 48 to perform an interpolating operation between various processing operations in path search processor 46. Interpolating filter 48 has been provided with interpolating filters corresponding to a plurality of oversampling numbers. Interpolating filter 48 is capable of performing interpolation operation at a plurality of chip intervals when the oversampling number is changed by the interpolation position control signal. Alternatively, interpolating filter 48 may employ the structure shown in Fig. 3 where the oversampling number is "2" and the tap length is "4", and may be looped twice to perform an interpolation process where the oversampling number is "4",

for example, with an easy and simple arrangement.

Path controller 47 detects a peak in excess of a predetermined threshold from a delay profile that has been generated as a result of a path searching process in path search processor 46 where an interpolation process is inserted depending on an interpolation position control signal, and indicates a delay time corresponding to the detected peak to first finger 43₁.

In the present embodiment, a non-illustrated mobile terminal on a transmission side sends a framed transmission signal having a plurality of time slots. The transmission signal is received by base station apparatus 40. To each of the time slots, there is added a pilot signal at its leading position which represents a fixed pattern known to both transmission and reception sides. The pilot signal is quadrature-modulated together with the transmission data and thereafter spread over a spectrum using a spreading code inherent in each communication channel. Transmission signals that have been spread using respective inherent spreading codes according to the CDMA scheme are received at antenna 11. Receiver 12 performs signal interface conversion such as amplification and quadrature demodulation. Here, the signal interface conversion is conversion such as multiplication of a reception signal by a reference frequency which is generated by a reference frequency generator, not shown,

with a multiplier to convert the reception signal into a baseband signal.

Parameter manager 41 is capable of allotting the reception signal to fingers 43_1 to 43_N and searchers 42_1 to 42_N for respective communication channels included in the reception signal. For example, parameter manager 41 allots unused fingers and searchers, successively from first finger 43_1 and first searcher 42_1 , to the reception signal. Then, parameter manager 41 indicates code generating information for generating corresponding spreading codes to the allotted fingers and searchers. The fingers and searchers are constructed such that they generate spreading codes that are associated with the code generating information indicated thereto.

Demodulated signals demodulated by receiver 12 are supplied to those of N searchers 42_1 to 42_N which have been allotted by parameter manager 41 and those of N fingers 43_1 to 43_N which have been allotted by parameter manager 41.

Interpolation position controller 44 refers to code generating information indicated by parameter manager 41 to recognize the number of communication channels.

Interpolation information which represents whether an interpolation process is to be inserted or not and the oversampling number at the time when an interpolation process is to be inserted has been stored in interpolation position controller 44 has registered corresponding to the

recognized number of communication channels.

Interpolation position controller 44 outputs the interpolation information corresponding to the recognized number of communication channels as interpolation position
5 indicating information to each communication channel portion.

First searcher 42₁ interpolates sampling points in order to reduce chip intervals of the reception signal, and generates a delay profile based on a pilot signal
10 added to the leading position of each time slot of the interpolated signal. In the delay profile, the power values of reception signal components which are orthogonal to each other that are demodulated by receiver 12 are calculated for respective delay times. Usually, the power
15 values calculated for the respective delay times on the delay profile represent peaks on a plurality of different propagating paths due to multipath fading. First searcher 42₁ then detects peaks in excess of a predetermined threshold, and indicates delay times corresponding to the
20 respective detected peaks to first finger 43₁ associated with first searcher 42₁. First finger 43₁ then extracts paths of received waves corresponding to the indicated delay times from the demodulated signals demodulated by receiver 12. These extracted paths are then estimated for
25 channels by detector 54 for removal of the effect of fading to a certain extent, and are RAKE-combined and then

subjected to a predetermined reception processing in reception processor 16.

Fig. 6 schematically shows an arrangement of an essential portion of first searcher 42₁ and interpolation position controller 44 which correspond to the path searching apparatus according to the first embodiment of the present invention. Path search processor 46 of first searcher 42₁ comprises code generator 45 for generating a spreading code for a communication channel allotted to first searcher 42₁, correlation value calculator 21, in-phase adder 22, and power adder 23. The searcher according to the present embodiment resides in that it can select whether an interpolation process performed by interpolating filter 48 is to be inserted between various processors of path search processor 46 or not, based on interpolation position indicating information indicated from interpolation position controller 44. To perform the above function, each searcher has four selectors 61 to 64. Interpolating filter 48 comprises four filters 65 to 68 depending on the details of its interpolation process.

While interpolating filter 48 inserted in a path searching process comprises four filters 65 to 68 that are selectively used depending on the details of its interpolation process in the illustrated embodiment, one filter may be used as interpolating filter 48 in each process. At any rate, any filter may desirably be

arranged within interpolating filter 48 insofar as it can perform an interpolation process between various processes depending on the interpolation position indicating information.

5 First selector 61 is supplied with a demodulated signal demodulated by receiver 12 and an output signal from first filter 65 which has been interpolated to reduce the chip interval of the demodulated signal, and alternatively selects one of the supplied signals based on
10 the interpolation position indicating information, as a first selected output signal that is supplied to correlation value calculator 21.

Second selector 62 is supplied with a correlation value calculated by correlation value calculator 21 and an
15 output signal from second filter 66 which has been interpolated to reduce the chip interval of the correlation value calculated by correlation value calculator 21, and alternatively selects one of the supplied signals based on the interpolation position
20 indicating information, as a second selected output signal that is supplied to in-phase adder 22.

Third selector 63 is supplied with an in-phase addition result calculated by in-phase adder 22 and an output signal from third filter 67 which has been
25 interpolated to reduce the chip interval of the in-phase addition result calculated by in-phase adder 22, and

alternatively selects one of the supplied signals based on the interpolation position indicating information, as a third selected output signal that is supplied to power adder 23.

5 Fourth selector 64 is supplied with a power addition result calculated by power adder 23 and an output signal from fourth filter 68 which has been interpolated to reduce the chip interval of the power addition result calculated by power adder 23, and alternatively selects
10 one of the supplied signals based on the interpolation position indicating information, as a fourth selected output signal that is supplied to path controller 47.

Correlation value calculator 21 detects pilot signals added to the leading positions of respective time slots of
15 the input signal, and calculates a correlation value between the detected pilot signal and an ideal reception signal which are produced by multiplying and spreading a spreading code generated by code generator 45 and a predetermined pilot signal. In-phase adder 22 performs a
20 certain number of in-phase additions " $I+I$ ", " $Q+Q$ " on an I signal and a Q signal, which are signal components orthogonal to each other, of the quadrature-demodulated pilot signal. Power adder 23 performs a certain number of power additions " I^2+Q^2 " on the signal components that have
25 been added in phase.

Interpolation position controller 44 for outputting

interpolation position indicating information comprises interpolation information memory 56 for storing the above interpolation information and number-of-communication-channel measuring unit 57 for measuring the number of communication channels to be processed based on the code generating information indicated by parameter manager 41. Here, number-of-communication-channel measuring unit 57 recognizes the number of communication channels to be processed from the code generating information indicated by parameter manager 41. However, number-of-communication-channel measuring unit 57 may recognize the number of communication channels from a despread signal which is produced by despread a reception signal. In this case, when despread is performed by using a spreading code other than the corresponding communication channel, the reception signal becomes almost "0" due to its orthogonal nature. Therefore, when a despread signal whose level is higher than a predetermined level is obtained for a communication channel, the communication channel can be recognized as a communication channel to be processed and it is possible to recognized the number of channels to be processed at respective time points. Interpolation information memory 56 stores interpolation information which comprises interpolation position specifying information 58 indicating whether an interpolation process is to be inserted or not and an

oversampling number 59 at the time an interpolation process is to be inserted, the interpolation information corresponding to the number of channels measured by number-of-communication-channel measuring unit 57.

5 Fig. 7 shows an example of interpolation information stored in interpolation information memory 56. In the interpolation information, interpolation position specifying information 58 indicating whether an interpolation process is to be inserted or not and an
10 oversampling number 59 at the time an interpolation process is to be inserted is registered, corresponding to the number of the communication channels (CH), for each of before and after the process of calculating a correlation value, the process of performing an in-phase addition, and
15 the process of performing a power addition, which are carried out by path search processor 46.

For example, when the number of channels to be processed which is measured by number-of-communication-channel measuring unit 57 is "1", before a correlation
20 value is calculated and before an in-phase addition is performed with the corresponding interpolation position specifying information of "interpolation", interpolation information for performing an interpolation process with the oversampling number "2" is searched for. Similarly,
25 when the number of channels to be processed which is measured by number-of-communication-channel measuring unit

57 is "2", before a correlation value is calculated and after an in-phase addition is performed with the corresponding interpolation position specifying information of "interpolation", interpolation information for performing an interpolation process with the oversampling number "2" is searched for. When the number of channels to be processed which is measured by number-of-communication-channel measuring unit 57 is "3", before a correlation value is calculated and after a power addition is performed with the corresponding interpolation position specifying information of "interpolation", interpolation information for performing an interpolation process with the oversampling number "2" is searched for. As the number of communication channels to be processed is smaller, an interpolation process is thus performed as a pre-process to increase the number of interpolation processes for thereby increasing the accuracy for path detection when an extra amount of calculation is available.

The interpolation information searched for based on the number of channels to be processed which has been measured by number-of-communication-channel measuring unit 57 is indicated, as the interpolation position specifying information which is represented by a control signal having a certain format, to searchers 42_1 to 42_N . Though the interpolation position specifying information is illustrated as being indicated to only first searcher 42_1 ,

in the described which follows, it is actually indicated to a plurality of searchers depending on the reception signal.

Fig. 8 shows an example of a format structure of such interpolation position indicating information. Specifically, the interpolation position indicating information which is indicated to first searcher 42₁ is indicated as control information indicating, as a unit, interpolation position 61 where the interpolation position specifying information is "interpolation" and oversampling number 62 corresponding thereto. If there are a plurality of pieces of interpolation position specifying information which are "interpolation", then as many pieces of interpolation position indicating information as the number of pieces of interpolation position specifying information are indicated to first searcher 42₁. For example, when the number of channels to be processed is "1", then two pieces of interpolation position indicating information indicating that the interpolation position is "before correlation value calculation" and the oversampling number is "2" and that the interpolation position is "before in-phase addition" and the oversampling number is "2" are indicated to first searcher 42₁.

First searcher 42₁ which selects the insertion of an interpolation process into various operation processors in

path search processor 46 based on the interpolation
position indicating information indicated in the above
format has a CPU, not shown, and performs various control
processes based on a control program that is stored in a
5 given memory such as a ROM or the like.

Fig. 9 schematically shows the content of the
processing of a control program that is stored in such a
given memory. First searcher 42, first refers to the
interpolation position indicating information in the
10 format shown in Fig. 8 which is indicated from
interpolation position controller 44 to determine whether
there is an interpolation position before a correlation
value is calculated in step S70. If the interpolation
position is "before correlation value calculation", then
15 interpolating filter 48 having the structure shown in Fig.
3 interpolates a demodulated signal supplied from receiver
12 to reduce the chip interval thereof in step S71. To do
so, the oversampling number may be set to "2" in the
interpolating filter having the structure shown in Fig. 3.

20 If the interpolation position is not "before
correlation value calculation" in step S70, or after
performing the interpolation calculation in step S71,
correlation value calculator 21 calculates correlation
values of pilot signals which are added to the leading
25 positions of respective time slots and which are of a
predetermined fixed pattern, of I and Q signal components

that have been quadrature-demodulated and despread. Since the pilot signals are of a fixed pattern, they can be determined with accuracy as an ideal reception signal in the reception side. In correlation value calculator 21, a
5 correlation value with respect to an ideal reception signal generated from the pilot signal is calculated for each of the time slots of the received frame. As the correlation value is higher, the pilot signal at the leading position of each time slot is closer to an ideal
10 waveform, indicating a better reception sensitivity.

Next in step S73, first searcher 42₁ refers to the interpolation position indicating information indicated from interpolation position controller 44 to determine whether the interpolation position is "before in-phase
15 addition" or not. If the interpolation position is "before in-phase addition", then interpolating filter 48 interpolates the calculated correlation value to reduce the chip interval thereof in step S74, as with step S71.

If the interpolation position is not "before in-phase
20 addition" in step S73, or after performing interpolating operation in step S74, in-phase adder 22 adds signal components for the respective I and Q signal components for a given number of times N in step S75. Thus, noise components contained in the I and Q signals are removed.
25 The greater the number of in-phase additions, the smaller the noise in each of the signal components.

Next, in step S76, first searcher 42₁ refers to the interpolation position indicating information indicated from interpolation position controller 44 to determine whether the interpolation position is "after in-phase
5 addition is finished" or not. If the interpolation position is "after in-phase addition is finished", then interpolating filter 48 interpolates the calculated correlation value to reduce the chip interval thereof in step S77, as with step S71.

10 If the interpolation position is not "after in-phase addition is finished" in step S76, or after performing interpolating operation in step S77, power adder 23 adds power values for a given number of times M in step S78. The power values are thus averaged with respect to time,
15 preventing paths from being detected with wrong power values due to instantaneous noise.

Next, in step S79, first searcher 42₁ refers to the interpolation position indicating information indicated from interpolation position controller 44 to determine
20 whether the interpolation position is "after power addition is finished" or not. If the interpolation position is "after power addition is finished", then interpolating filter 48 interpolates the calculated correlation value to reduce the chip interval thereof in
25 step S80, as with step S71.

In the interpolation position is not "after power

addition is finished" in step S79, and/or when the
interpolating calculation has been performed in step S80,
the calculated power value becomes a delay profile
indicating the reception signal that is converted into
5 power values for respective delay times in a time series.
Then, in step S81, path controller 47 detects a peak in
excess of a predetermined threshold with respect to the
power value for each delay time, and indicates a delay
time corresponding to a peak in excess of the threshold to
10 first finger 43₁. Thereafter, the processing sequence is
put to an end.

As described above, the path searching apparatus
according to the first embodiment has interpolation
position controller 44 which has stored information
15 indicative of whether an interpolation process required to
increase the detection accuracy for a path search
depending on the number of communication channels to be
processed is to be inserted or not, and oversampling
numbers at the time an interpolation process is to be
20 inserted. The path searching apparatus can change whether
an interpolation process performed by interpolating filter
48 is to be inserted between various processors of path
search processor 46 or not, based on interpolation
information searched for depending on the number of
25 channels to be processed which has been measured by
number-of-communication-channel measuring unit 57. The

interpolation information is established such that as the number of communication channels to be processed is smaller, an interpolation process is performed as a pre-process to increase the number of interpolation processes.

5 Consequently, it is possible to solve the conventional problem of a minimum accuracy for path detection which is achieved because an interpolation process has been performed in a fixed processing position regardless of the number of channels to be processed even if the number of
10 communication channels is small and an extra amount of calculation available. The present embodiment can maintain a maximum amount of calculation depending on the number of channels to be processed for increasing the accuracy for path detection as much as possible when there
15 is an extra amount of calculation available.

Second Embodiment:

The path searching apparatus according to the first embodiment inserts an interpolation process in a processing position depending on the number of
20 communication channels during a path searching process, uniformly for each communication channel. On the contrary, according to a second embodiment, a path searching apparatus measures the quality of a reception signal in each communication channel and changes an interpolation
25 position for a communication channel whose reception quality is low for thereby increasing the accuracy for

path detection. The constitution of a base station apparatus to which the path searching apparatus according to the second embodiment is applicable is similar to that in the first embodiment. Therefore, the second embodiment
5 will be described below mainly with respect to the constitution of a searcher and an interpolation position controller.

Fig. 10 schematically shows an arrangement of an essential portion of a searcher and a interpolation
10 position controller which are the path searching apparatus according to the second embodiment. Here, the path searching apparatus has searcher 90, interpolation position controller 91, and reception quality measuring unit 92. If the path searching apparatus is applied to
15 the base station apparatus in a mobile communication system of the CDMA scheme shown in Fig. 5, then searcher 90 corresponds to each of N searchers 42_1 to 42_N shown in Fig. 5 and interpolation position controller 91 corresponds to interpolation position controller 44 shown
20 in Fig. 5. Reception quality measuring unit 92 is provided in the base station apparatus for being shared by the searchers.

Reception quality measuring unit 92 is supplied with signal-to-interference ratio (SIR) values 94 calculated by
25 RAKE combiners of the respective searchers and monitors reception qualities in respective communication channels.

Furthermore, reception quality measuring unit 92 determines the reception quality level of a reception quality which is calculated by comparison with a plurality of predetermined thresholds, and indicates the reception
5 quality level of a communication channel which is lower than a certain reception quality level and a communication channel number for identifying the communication channel, to interpolation position controller 91.

Interpolation position controller 91 has
10 interpolation information corresponding to a plurality of reception quality levels in addition to the interpolation information shown in Fig. 7. In the interpolation information corresponding to the reception quality levels, interpolation position specifying information indicating
15 whether an interpolation process is to be inserted or not between various processes during a path searching process shown in Fig. 7, and an oversampling number at the time an interpolation process is performed has been stored in advance. Interpolation position controller 91 is supplied
20 with the number of communication channels 95 to be processed from parameter manager 41 and also specified with communication channels whose reception quality levels are lower than a predetermined level from reception quality measuring unit 92. Interpolation position
25 controller 91 searches for interpolation information depending on the number of communication channels which

has been measured by the number-of-communication-channel
measuring unit. With respect to a communication channel
whose reception quality is low which has been indicated
from reception quality measuring unit 92, interpolation
5 position controller 91 indicates interpolation information
depending on the reception quality level, rather than the
interpolation information searched for depending on the
number of communication channels which has been measured
by the number-of-communication-channel measuring unit, as
10 interpolation position indicating information to the
searchers in the respective communication channels. Based
on thus indicated interpolation position indicating
information, searcher 90 performs interpolating operation
on demodulated signal 96 at an optimum position, and
15 indicates a reception time instant to the finger.

Fig. 11 shows an example of the interpolation
position indicating information indicated from the
interpolation position controller. Interpolation position
indicating information 97 is indicated as control
20 information comprising, as a unit, interpolation position
99 where interpolation information specifying information
is "interpolation", and corresponding oversampling number
100, wherein communication channel number 98 for
identifying a communication channel is added to the
25 leading portion.

Searcher 90 has, in addition to the arrangement of

first searcher 42, shown in Fig. 6, a determining unit for determining whether the interpolation position indicating information indicated in the format shown in Fig. 11 is addressed to itself or not. The determining unit

5 determines the destination of the received interpolation position indicating information by comparing it with a communication channel number allotted in advance to its own searcher. If the received interpolation position indicating information is determined as being
10 interpolation position indicating information addressed to itself, then determining unit inserts an interpolation process between various processes during a path searching process depending on the interpolation position and the oversampling number which are included in the
15 interpolation position indicating information.

As described above, the path searching apparatus according to the second embodiment changes the position where an interpolation process is inserted during a path searching process, depending on not only the number of
20 communication channels to be processed but also the reception quality level. Therefore, for a communication channel whose reception quality level is low, an interpolation process is inserted at a position for more interpolation processes so as to be able to carry out an
25 accurate control process to achieve an increase in the accuracy for path detection.

In each of the above embodiments, the position for performing an interpolation process is changed. However, the present invention is not limited to such processing details. In the above embodiments, correlation value
5 calculations, in-phase additions, and power additions are performed as a path searching process. However, the present invention is not limited to such processing details.

In each of the above embodiments, the interpolation
10 position is changed depending on the communication channel. However, the present invention is not limited to such processing details. In view of the fact that one user may possibly use a plurality of communication channels, the interpolation position may be changed depending on the
15 number of users.

In the above embodiments, the interpolation information is composed of the interpolation position specifying information and the oversampling number. However, the present invention is not limited to such
20 processing details. For example, by setting the oversampling number to "2" in advance with the interpolating filter, the interpolation information memory may store only interpolation position specifying information for each communication channel or each
25 reception quality level.

Industrial applicability:

According to the present invention, as described above, the position for performing an interpolation process to increase the accuracy of a delay profile depending on the number of communication channels to be
5 processed is changed to detect a path with optimum accuracy depending on a reception processing situation.

The insertion of an interpolation process may be selected before and after correlation value calculation, in-phase addition, and power addition for the generation
10 of the delay profile. Therefore, in view of a trade-off between an increase in the amount of calculation due to the insertion of an interpolation process and an accuracy for path detection, the amount of calculation and the accuracy for path detection can be set to optimum values
15 depending on the number of communication channels to be processed, making it possible to effectively utilize various resources of the apparatus.

An interpolation process for generating a delay profile is inserted at a position depending on the
20 reception quality of each communication channel that has actually been measured, so that the position for performing an interpolation process can accurately be controlled for each communication channel, and the accuracy for path detection can be increased more flexibly
25 depending on the reception quality.

The oversampling number for specifying a chip

interval is included in interpolation information for controlling a finer interpolation process.

By increasing the number of interpolation processes when the amount of processing to be calculated is smaller,
5 the accuracy for path detection can be increased by an extra calculation capability when the number of communication channels is small.

CLAIMS

1. A method of searching for a path, comprising:
- a first interpolating step of interpolating a demodulated signal to generate a first interpolated signal;
- 5 a first selecting step of generating a first selected signal by alternatively selecting said first interpolated signal or said demodulated signal based on interpolation information, said interpolation information indicating whether an interpolation process for reducing a chip
- 10 interval is to be performed or not between processes for generating a delay profile which indicates a temporal change of reception time instants of said demodulated signal due to multipath fading;
- a correlation value calculating step of calculating a
- 15 correlation value between a pilot pattern which is included in said first selected signal and has a predetermined fixed pattern and a predetermined expected value;
- a second interpolating step of interpolating the
- 20 correlation value calculated in said correlation value calculating step to generate a second interpolated signal;
- a second selecting step of generating a second selected signal by alternatively selecting said second interpolated signal and said correlation value based on

25 said interpolation information;

an in-phase adding step of adding in-phase components of said second selected signal for a predetermined number of times;

30 a third interpolating step of interpolating an in-phase addition sum calculated in said in-phase adding step to generate a third interpolated signal;

a third selecting step of generating a third selected signal by alternatively selecting said third interpolated signal or said in-phase addition sum based on said
35 interpolation information;

a power adding step of adding power values calculated from signal components of said third selected signal for a predetermined number of times;

40 a fourth interpolating step of interpolating a power addition sum calculated in said power adding step to generate a fourth interpolated signal;

a fourth selecting step of generating a fourth selected signal by alternatively selecting said fourth interpolated signal or said power addition sum based on
45 said interpolation information; and

a path detecting step of detecting a path in excess of a predetermined threshold based on said fourth selected signal.

2. A method of searching for a path according to

claim 1, wherein said interpolation information comprises
information indicative of whether said interpolation
process is to be performed or not, depending on the number
5 of communication channels to be processed.

3. A method of searching for a path according to
claim 1, wherein said interpolation information comprises
information indicative of whether said interpolation
process is to be performed or not, depending on reception
5 quality measured in each communication channel of said
demodulated signal.

4. A method of searching for a path according to
claim 1, wherein said interpolation information comprises
information indicative of whether said interpolation
process is to be performed or not, depending on the number
5 of communication channels to be processed and reception
quality measured in each communication channel of said
demodulated signal.

5. A method of searching for a path according to
claim 1, wherein said demodulated signal comprises a
signal produced by converting a reception signal of a CDMA
(Code Division Multiple Access) system into a baseband
5 signal and processing the baseband signal by way of
quadrature demodulation.

6. An apparatus for searching for a path,
comprising:

path searching means for generating a delay profile
based on a pilot signal which is included in each time
5 slot and has a fixed pattern, according to a path
searching process composed of a plurality of processing
units, said delay profile indicating a temporal change of
reception time instants due to multipath fading of a
demodulated signal;

10 interpolation information storage means for storing
interpolation information which indicates whether an
interpolation process for reducing a chip interval is to
be performed or not before and after each of the
processing units;

15 interpolation position processing control means for
enabling said path searching means to perform an
interpolation process before and after each of the
processing units based on said interpolation information;
and

20 path detecting means for detecting a reception path
based on the delay profile generated by said path
searching means.

7. An apparatus for searching a path according to
claim 6, wherein said interpolation information comprises

information indicative of whether the interpolation
process for reducing a chip interval is to be performed or
5 not, depending on the number of communication channels to
be processed.

8. An apparatus for searching a path according to
claim 6, wherein said interpolation information comprises
information indicative of whether the interpolation
process for reducing a chip interval is to be performed or
5 not, depending on the reception quality measured in each
communication channel of said demodulated signal.

9. An apparatus for searching a path according to
claim 6, wherein said interpolation information comprises
information indicative of whether said interpolation
process is to be performed or not, depending on the number
5 of communication channels to be processed and the
reception quality measured in each communication channel
of said demodulated signal.

10. An apparatus for searching for a path,
comprising:

interpolation information storage means for storing
interpolation information indicative of whether an
5 interpolation process for reducing a chip interval between
processes for generating a delay profile is to be

performed or not, said delay profile indicating a temporal change of reception time instants of a demodulated signal due to multipath fading;

10 first interpolating means for interpolating said demodulated signal to generate a first interpolated signal;

 first selecting means for generating a first selected signal by alternatively selecting said first interpolated
15 signal or said demodulated signal based on said interpolation information;

 correlation value calculating means for calculating a correlation value between a pilot pattern which is included in said first selected signal and has a
20 predetermined fixed pattern and a predetermined expected value;

 second interpolating means for interpolating the corrected value calculated by said correlation value calculating means to generate a second interpolated
25 signal;

 second selecting means for generating a second selected signal by alternatively selecting said second interpolated signal and said correlation value based on said interpolation information;

30 in-phase adding means for adding in-phase components of said second selected signal for a predetermined number of times;

third interpolating means for interpolating an in-phase addition sum calculated by said in-phase adding
35 means to generate a third interpolated signal;
third selecting means for generating a third selected signal by alternatively selecting said third interpolated signal or said in-phase addition sum based on said interpolation information;
40 power adding means for adding power values calculated from signal components of said third selected signal for a predetermined number of times;
fourth interpolating means for interpolating a power addition sum calculated in said power adding means to
45 generate a fourth interpolated signal;
fourth selecting means for generating a fourth selected signal by alternatively selecting said fourth interpolated signal or said power addition sum based on said interpolation information; and
50 path detecting means for detecting a path in excess of a predetermined threshold based on said fourth selected signal.

11. An apparatus for searching for a path according to claim 10, wherein said interpolation information comprises information indicative of whether the interpolation process for reducing a chip interval is to
5 be performed or not, depending on the number of

communication channels to be processed.

12. An apparatus for searching for a path according to claim 10, wherein said demodulated signal comprises a signal produced by converting a reception signal of a CDMA (Code Division Multiple Access) system into a baseband
5 signal and processing the baseband signal by way of quadrature demodulation.

13. An apparatus for searching for a path according to claim 10, further comprising reception quality measuring means for measuring a reception quality in each communication channel of said demodulated signal, wherein
5 said interpolation information comprises information indicative of whether the interpolation process for reducing a chip interval is to be performed or not, depending on the reception quality measured in each communication channel of said demodulated signal.

14. An apparatus for searching for a path according to claim 10, further comprising reception quality measuring means for measuring a reception quality in each communication channel of said demodulated signal, wherein
5 said interpolation information comprises information indicative of whether the interpolation process for reducing a chip interval is to be performed or not,

depending on the number of communication channels to be
processed and the reception quality measured in each
10 communication channel of said demodulated signal.

15. An apparatus for searching for a path according
to claim 10, wherein said interpolation information
comprises interpolation position specifying information
indicative of whether the interpolation process for
5 reducing a chip interval is to be performed or not
depending on the number of communication channels to be
processed between processes for generating said delay
profile, and an oversampling number, wherein each of said
first to fourth selecting means makes an alternative
10 selection based on said interpolation position specifying
information, and wherein each of said first to fourth
interpolating means performs an interpolation based on the
corresponding oversampling number.

16. An apparatus for searching for a path according
to claim 11, wherein said interpolation information is set
to perform the interpolation process between processes for
achieving more interpolation processes as the number of
5 communication channels to be processes is smaller.

17. An apparatus for searching for a path according
to claim 15, wherein said interpolation information is set

to perform the interpolation process between processes for
achieving more interpolation processes as the number of
5 communication channels to be processes is smaller.




Fig. 1




Fig. 4




Fig. 2




Fig. 3

10/031346




Fig. 5

10/031346




Fig. 6

10/031346

Interpolation position	Number of channels		
	1	2	3
Before corre- lation value calculation	Interpolation Oversampling number "2"	Interpolation Oversampling number "2"	Interpolation Oversampling number "2"
Before in-phase addition	Interpolation Oversampling number "2"	No Interpolation	No Interpolation
After in-phase addition is finished	No Interpolation	Interpolation Oversampling number "2"	No Interpolation
After power addition is finished	No Interpolation	No Interpolation	Interpolation Oversampling number "2" ~ 58 ~ 59

Fig. 7




Fig. 8




Fig. 10




Fig. 11




Fig. 9

DECLARATION AND POWER OF ATTORNEY

As a below named inventor, I HEREBY DECLARE:

THAT my residence, post office address, and citizenship are as stated below next to my name;

THAT I believe I am the original, first, and sole inventor (if only one inventor is named below) or an original, first, and joint inventor (if plural inventors are named below or in an attached Declaration) of the subject matter which is claimed and for which a patent is sought on the invention entitled

METHOD OF AND APPARATUS FOR PATH SEARCH

the specification of which (check one)

 X is attached hereto.

 X was filed on July 21, 2000 as United States Application Number
or PCT International Application Number PCT/JP00/04882
and was amended on _____ (if applicable).

THAT I do not know and do not believe that the same invention was ever known or used by others in the United States of America, or was patented or described in any printed publication in any country, before I (we) invented it;

THAT I do not know and do not believe that the same invention was patented or described in any printed publication in any country, or in public use or on sale in the United States of America, for more than one year prior to the filing date of this United States application;

THAT I do not know and do not believe that the same invention was first patented or made the subject of an inventor's certificate that issued in any country foreign to the United States of America before the filing date of this United States application if the foreign application was filed by me (us), or by my (our) legal representatives or assigns, more than twelve months (six months for design patents) prior to the filing date of this United States application;

THAT I have reviewed and understand the contents of the above-identified specification, including the claim(s), as amended by any amendment specifically referred to above;

THAT I believe that the above-identified specification contains a written description of the invention, and of the manner and process of making and using it, in such full, clear, concise, and exact terms as to enable any person skilled in the art to which it pertains, or with which it is most nearly connected, to make and use the invention, and sets forth the best mode contemplated by me of carrying out the invention; and

THAT I acknowledge the duty to disclose to the U.S. Patent and Trademark Office all information known to me to be material to patentability as defined in Title 37, Code of Federal Regulations, §1.56.

I HEREBY CLAIM foreign priority benefits under Title 35, United States Code § 119(a)-(d) or § 365(b) of any foreign application(s) for patent or inventor's certificate, or § 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below any foreign application for patent or inventor's certificate or of any PCT international application having a filing date before that of the application on which priority is claimed.

Prior Foreign Application Number	Country	Foreign Filing Date	Priority Claimed?	Certified Copy Attached?
11-205471	Japan	21/07/1999	Yes	

I HEREBY CLAIM the benefit under Title 35, United States Code § 119(e) of any United States provisional application(s) listed below.

U.S. Provisional Application Number	Filing Date

I HEREBY CLAIM the benefit under Title 35, United States Code, § 120 of any United States application(s), or § 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application in the manner provided by the first paragraph of Title 35, United States Code, § 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

U.S. Parent Application Number	PCT Parent Application Number	Parent Filing Date	Parent Patent Number

I HEREBY APPOINT the following registered attorneys and agents of the law firm of FOLEY & LARDNER to have full power to prosecute this application and any continuations, divisions, reissues, and reexaminations thereof, to receive the patent, and to transact all business in the United States Patent and Trademark Office connected therewith:

STEPHEN A. BENT	Reg. No. 29,768
DAVID A. BLUMENTHAL	Reg. No. 26,257
BETH A. BURROUS	Reg. No. 35,087
ALAN I. CANTOR	Reg. No. 28,163
WILLIAM T. ELLIS	Reg. No. 26,874
JOHN J. FELDHAUS	Reg. No. 28,822
MICHAEL D. KAMINSKI	Reg. No. 32,904

LYLE K. KIMMS	Reg. No. 34,079
KENNETH E. KROSIN	Reg. No. 25,735
JOHNNY A. KUMAR	Reg. No. 34,649
JACK LAHR	Reg. No. 19,621
GLENN LAW	Reg. No. 34,371
PETER G. MACK	Reg. No. 26,001
STEPHEN B. MAEBIUS	Reg. No. 35,264
BRIAN J. MC NAMARA	Reg. No. 32,789
SYBIL MELOY	Reg. No. 22,749
RICHARD C. PEET	Reg. No. 35,792
GEORGE E. QUILLIN	Reg. No. 32,792
ANDREW E. RAWLINS	Reg. No. 34,702
BERNHARD D. SAXE	Reg. No. 28,665
CHARLES F. SCHILL	Reg. No. 27,590
RICHARD L. SCHWAAB	Reg. No. 25,479
MICHELE M. SIMKIN	Reg. No. 34,717
HAROLD C. WEGNER	Reg. No. 25,258

and I request that all correspondence be directed to:


Customer No. 22428

DAVID A. BLUMENTHAL
FOLEY & LARDNER
Washington Harbour
3000 K Street, N.W., Suite 500
Washington, D.C. 20007-5109

Telephone: (202) 672-5300
Facsimile: (202) 672-5399

I UNDERSTAND AND AGREE THAT the foregoing attorneys and agents appointed by me to prosecute this application do not personally represent me or my legal interests, but instead represent the interests of the legal owner(s) of the invention described in this application.

I FURTHER DECLARE THAT all statements made herein of my own knowledge are true, and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

Name of first inventor	<u>Sei HIRADE</u>
Residence	<u>Tokyo, Japan JPX</u>
Citizenship	<u>Japan</u>
Post Office Address	<u>c/o NEC Corporation, 7-1, Shiba 5-chome, Minato-ku, Tokyo-108-8001, Japan</u>
Inventor's signature	<u>Sei Hirade</u> 
Date	<u>January 11, 2002</u>